

DX900 WWE OS Version 553 Update Notification

What's New in DX900 OS 553

Base on OS 551, we improved the battery life in this version

Bug fixed

Fixed the GPS cause abnormal power consumption

Required files:

1. EUU_ACER_DX900_WWE_A147_040_0553_1200D4CB.exe
2. ModemUpdater_3306_AT6.exe (This is update file for 3G firmware)
3. 2577(DX900_0410_V127).rar (This is update file for Battery IC Firmware)

Update procedure:

1. Please update DX900 OS version 553 first
2. Then update 3G Firmware Update
3. Then update Battery IC Firmware

Normal operation steps:

OS Update:

Make sure use PC with XP system (better with service pack2) or Vista for OS updating.

- Disable all kind of firewall before OS updating.
- Be sure your PC or laptop already installed ActiveSync 4.5 or above version
- Connect DX900 and your PC via USB cable and be sure the ActiveSync is activated with GREEN sign.
 - If Activesync is hard to connect, you can go start/setting/connection/ **USB to PC** and disable the “advanced network functionality”, then Activesync would be easily connecting.
- Please backup all necessary data on PC side before OS updating process.
- Be sure the power adapter is properly connection during the updating process.
- Run EUU file and following the instructions show on screen to complete OS updating.

3G Firmware Update

- Copy ModemUpdater_3306_AT6.exe to your DX900
- Double click ModemUpdater_3306_AT6.exe
- Follow on-screen instruction to complete the update.

- Reset DX900.
- Go to Start > Settings > System > System Information > Wireless Module > GSM/GPRS > Firmware Version The correct version should be R4AEC2_3306_V2.06AT6
- If the above version is incorrect, please repeat the above steps to update again.

Battery IC Firmware Update

- Prepare one micro SD card and format it
- Extract 2577(DX900_0410_V127).rar
- Copy the folder 2577 into micro SD card
- Remove the battery cover and do not install back until all the process finished
- Make sure the battery is installed **and AC adapter is connected.**
- Power on the device and wait for the Today screen is ready
- Insert the micro SD card
- The installation will launch automatically.
- Wait for the message "Update battery firmware finish"
- Remove the battery **(Must remove the battery before you proceed the next step)**
- Remove the AC Adapter
- Wait for 10 seconds then install the battery.
- Power on the device.